

快/慢速阻尼振荡波抗扰度

测试标准:

IEC 61000-4-18

GB/T17626.18

DOW-CG1 S

慢速阻尼震荡波

8种菜单语言，可选

7英寸电容式触摸显示屏

连接方式：千兆以太网、USB、RS485

频率：100 kHz, 1 MHz \pm 10 %

输出电压：0.2 kV – 4.4 kV \pm 10 %

输出电流：1 A – 22 A \pm 20 %

输出阻抗：200 Ω

上升时间：75ns \pm 20%

衰减电压波形 Pk5 p $\frac{1}{2}$:Pk1, Pk10< $\frac{1}{2}$:Pk1

脉冲重复：最大 100 kHz, 50/ s

脉冲重复：1 MHz 最大 500/ s

突发持续时间：1 ms–20 s, 100 kHz, @1 MHz

突发重复：100ms–200s, 100 千赫, @1 兆赫

内置三相耦合去耦网络

EUT AC max. 3 x 690 V L-L (400 V L-N)

EUT AC max. 3 x 32 A

EUT DC max. 500 V, 32 A L-L or L-PE



DOW-CG1-F

快速阻尼震荡波

频率：3 MHz, 10 MHz, 30 MHz \pm 10 %

输出电压：0.4kV – 4.4 kV \pm 10 %

输出阻抗：50 Ω

上升时间：5 ns \pm 30%

衰减电压波形：Pk5 p $\frac{1}{2}$ ·Pk1, Pk10< $\frac{1}{2}$ ·Pk1

脉冲重复：< 330 ns @ 3 MHz

< 100 ns @ 10 MHz

< 33 ns @ 30 MHz

突发持续时间：1 ms–20 s

突发重复：10ms–200s

内置三相耦合去耦网络

EUT AC max. 3 x 690 V L-L (400 V L-N)

EUT AC max. 3 x 32 A

EUT DC max. 500 V, 32 A L-L or L-PE



<p>DOW-CG1-S-F</p>	<p>快/慢速阻尼震荡波 频率：100 kHz, 1 MHz, 3 MHz, 10 MHz, 30 MHz \pm 10 % 输出电压：0.4kV – 4.4 kV \pm 10 % 输出阻抗：50Ω 上升时间：5 ns\pm30% 衰减电压波形：Pk5 p$\frac{1}{2}$·Pk1, Pk10<$\frac{1}{2}$·Pk1 脉冲重复：< 330 ns @ 3 MHz < 100 ns @ 10 MHz < 33 ns @ 30 MHz 突发持续时间：1 ms–20 s 突发重复：10ms–200s 内置三相耦合去耦网络 EUT AC max. 3 x 690 V L-L (400 V L-N) EUT AC max. 3 x 32 A EUT DC max. 500 V, 32 A L-L or L-PE</p>	
<p>CDN-DOW-DATA-LF</p>	<p>8 线低速 I/O 线的手动 CDN。4.4KV, IEC61000-4-18 或 IEC60255-27。 EUT 最大 250V/4A AC/DC</p>	

<p>CDN-DOW-DATA-HF18</p>	<p>用于8条高速 I/O 线的手动 CDN。4.4KV, IEC61000-4-18。 EUT 最大电压为 60V/1A AC/DC。 对于 1 Gbps, 需要 2个适配器盒。</p>	 <p>The image shows a rack-mounted device labeled 'CDN-DOW-DATA-HF18'. It features a blue front panel with 16 ports arranged in two columns of eight. The left column ports are labeled 01 through 08, and the right column ports are labeled 09 through 16. Above the ports, there are several indicator lights and labels: 'Power 1', 'Power 2', 'SHDN', 'LOW', 'FE', and a warning symbol. To the right of the ports, there are two columns of green ports labeled '4 Lines' and '8 Lines', with a 'COUPLING' label between them. The device is mounted on a metal rack with visible screws.</p>
<p>ADAPTER BOX RJ45-8L</p>	<p>RJ45 适配器, 用于 CDN-DOW-DATA-HF 或-HF18。需要 2 件</p>	



兆騏方案（香港）有限公司

电话：+(852)30626685

邮箱：sales@leso.hk

地址：香港金鐘金鐘道89號力寶中心第1座10樓1003室